

CS306 SIX CHANNEL LAPTOP MIXER

Cooper Sound Systems, Inc. presents the CS306 Laptop Mixer. The CS306 comes standard with six mono input channels, four main outputs and the essential communication features required by professional sound crews. Cooper Sound has been providing top quality location sound equipment to the film and television industry since 1989.

FEATURES

- Multi track outputs-six prefade & two mix bus outputs on a standard D_{sub}25 connector
- Flexible routing. All six channels may be independently assigned to any combination of the four outputs.
- Meter bridge with high-intensity LEDs and illuminated switches that easily identify critical input settings
- Two monitor outs (with private line)
- Highest quality components: P&G faders, sealed potentiometers, durable, weather resistant all metal chassis with deep image labeling
- Ergonomically laid out for operator convenience and ease of operation
- Compact size - fits in a Pelican 1520 case



OPTIONS

Stereo linking & M/S Decode for any pair of inputs

SPECIFICATIONS

Internal Power: Eight 'AA' cells
External Power: 4-pin XLR (10-18V DC)
Power Consumption: < 4 Watts
THD + N: .003%
EIN: -129 dBu linear, -131 dBu 'A' wt'd
Weight (without batteries): 9.5 lbs / 4.3 kg
Size: 11.5" x 10.8" x 4.0"
(292mm x 274mm x 102mm)

Specifications subject to change without notice
Made in U.S.A



REAR PANEL

COOPER SOUND
SONUS CLARUS™

Cooper Sound Systems, Inc. 645 Main Street, Suite C Morro Bay, CA 93442-2273 USA

Phone: (805) 772-1007 Fax: (805) 772-1098

<http://www.coopersound.com>

April 2006